

FLEXPOWER GLOBAL™



FPG100 | 100W | 8A @ 12V, 4A @ 24VDC

- **Universal Input** global operation
- **FAI** built in Fire Alarm Interface
- **NetLink™** network interface
- **Locksafe™** tight regulation provides longterm lock protection
- **OutSmart™** Bi-color output LED verifies voltage setting
- **SureCharge™** Micro processor controlled battery charger
- **DPM™** RS485 Interface for Distributed Power Monitoring

Ordering

FPG100-Boxed Power supply/charger board

AGENCY APPROVALS

- CE (Europe)
- UL/ULC (Americas)
- BIS (India)
- PSE (Japan)
- RCM (Australia/NZ)
- IEC 62368-1:2014, EN55032:2015, EN61000-3-2:2014
- EN61000-3-3:2013, EN55024:2010 +A1:2015
- ROHS 3 Leadfree

OVERVIEW

The FPG100 is a universal input offline switchmode power supply-battery charger rated for 8A/12V or 4A/24V DC.

Complete fault detection and reporting is via independent AC Fault and System Fault form C relay contacts. A built-in Fire Alarm Interface allows unlocking of doors on a fire alarm condition.

Features:

- **Universal input** global operation
- **Low battery cutoff** protects batteries from deep discharge
- **Dedicated fast charger** prolongs battery life
- **Enhanced surge immunity** for input/output protection
- **Network ready** communicates with NetLink network module locally or via RS485
- **Lifetime Warranty** LifeSafety Power's quality commitment

SYSTEM SPECIFICATIONS

Input:

100 - 240 Vac +/- 10%, 50/60Hz | 156 Watts maximum

Output:

4A @ 24VDC | 8A @ 12VDC

- Overload & short circuit protection with auto-restart
- Bi-color LED: Blue (24VDC) | Green (12VDC)

Battery Backup:

- Autoswitch to battery with zero transfer time
- Built in fast charger at 1.1A charge current
- Low power cutoff to prevent battery deep discharge
- Reverse battery protection

Supervision:

- AC fail, System fault (form "C")
- Low power shutdown when battery voltage too low

Visual Indicators:

- AC On, DC output, System Fault, Fire Alarm

Mechanical specifications:

- Board: 210L x 140W x 60H mm | 8.25L x 5.5W x 2.4H"
- Removable metal housing

ELECTRICAL RATINGS

Parameter	Rating
Input Voltage	100 - 240 Vac +/- 10%, 50/60Hz
Input Power (max)	153W 2A Power Factor >0.9
Main Output	8Amps @ 12V or 4Amps @ 24V
Maximum Charge Current	1.1 Amp / 0.55A Selectable
Low Power Disconnect	at 70% of battery voltage
System BTU/Hr	85
Operating Temperature	-4 to +122F (-20 to +50C)
Efficiency	81% 120VAC 60Hz In, Full Load

FlexPower Global FPG100 Smart Power Supply/Charger

8 Amps @ 12VDC or 4 Amps @ 24VDC | FAI | Network ready

[LifeSafety Power.com](https://www.lifesafetypower.com)

(888) 577-2898

info1@lifesafetypower.com

Specifications subject to change without notice.

© 2023 LifeSafety Power. All rights reserved. LifeSafety Power, FlexPower, FlexPower Global and NetLink are trademarks of LifeSafety Power. All other trademarks and copyrights are the property of their respective owners.

P01-1005A 01/23

LifeSafety Power
10027 S. 51st Street, Suite 102
Phoenix, AZ 85044 USA