



ELECTRICAL RATINGS

Parameter	Rating
Input Voltage	120 VAC, 50/60Hz
Input Power (max)	170W
Output Power	150W
Maximum Charge Current	FPO150: 2A, 80AH maximum
Low Power Disconnect	at 70% of battery voltage
Systems BTU/Hr	66 BTU/Hr
Operating Temperature	32 to 122F (0 to +50C)
Efficiency	88% 120VAC 60Hz In, Full Load
Agency Approvals	UL294, UL603, UL1076, ULC S318, ULC S319, CSA C22.2 #205, FCC Part 15, Subpart B, CSFM IEC 62368-1:2014, EN 55032:2015, EN6100-3-2:2014, EN6100-3-3:2013, EN55024:2010+A1:2015, BIS IS13252(Part 1):2010, REACH 209, ROHS 3

OVERVIEW

Standard Power Systems provide FlexPower power modules in a secure UL listed solution. Standard Power features include:

- **Built in Fire Alarm disconnect** unlocks doors on a fire alarm
- **Low battery cutoff** protects batteries from deep discharge
- **Dedicated fast charger** prolongs battery life
- **Enhanced surge immunity** for input/output protection
- **Locksafe** optimized voltages provide long-term lock protection
- **OutSmart** Visual LED notification (12V/Green, 24V/Blue)
- **Network ready** with optional LifeSafety Power NetLink® module
 - Monitor power supply and battery in NetLink dashboard
 - Remote test batteries
- **Lifetime Warranty** LifeSafety Power's quality commitment

SYSTEM DETAILS

- **1 x FPO150** 150W Total Output, 120 VAC Input, AC Fault and System Fault form C contacts may be triggered by low/no battery, short to earth ground, power supply failure, or blown fuse
- **1 x B100** Terminal block output is Class 2 power limited and jumper selectable for either a fixed 12VDC or an adjustable range between 5-18VDC at 4 amps maximum current
- **E2 Enclosure** Size: 20.0H x 16.0W x 4.5D in (50.80 x 40.64 x 11.43 cm)
 - **Enclosure E2**
- **System Weight** 15.50 lbs (7.03kg)

ORDERING

FPO150-B100E2

120 VAC, 150W

AGENCY LISTINGS

US | Canada | Mexico | Europe | UK | India | Australia | New Zealand | RoHS

